



Features

- Isolation between input and output.
- Current to Current conversion.
- DIN Rail mounting.

Specification

- Input: 0 to 5A AC
- Output: 4 to 20 mA.
- Supply: 100 To 250V AC(SMPS)
- Optical Isolation between Input & Output.
- Accuracy: $\pm 1\%$ FSD.
- Size: 76X 27 X 116 mm.
- Operating temperature: 0 to 50 °C

Application

- I to I Converter: Can be used as current (0 to 5A AC) to current (4-20 mA) converter.
- Isolator: Can be used to optically isolate any costly instrument from input.
- Single channel output: Can be used to drive instrument with input specification (0 to 5A AC) by connecting them to output channel. Say instrument, which accepts 4 to 20 mA input can be connected to the output of the isolator.

Ordering information

- Input : 0 to 5A AC
- Output: 4 to 20 mA
- Supply: 100 To 250V AC(SMPS)